



- Battery charger with TRONIC technology for WET, GEL, AGM, MF, PbCa, EFB 12/24V batteries.
- BOOST (fast charge) function.
- Loading current display, protection against pole inversion, short circuit.

## TECHNICAL DATA

CODE	<b>807540</b>	CHARGING VOLTAGE	<b>12 / 24 V</b>	MAX.RATED REFERENCE CAPAC.	<b>225 / 180 Ah</b>
SINGLEPHASE MAINS VOLTAGE	<b>230 V</b>	EFFICIENT CHARGING CURRENT	<b>18 / 12 A</b>	ADJUSTMENT POSITIONS	<b>4</b>
MAINS FREQUENCY	<b>50 / 60 Hz</b>	RATED CHAR.CUR.EN60335-2-29	<b>12 / 8 A</b>	DIMENSIONS (LxWxH)	<b>22,5 x 29 x 20,5 cm</b>
CHARGING ABSORBED POWER	<b>300 W</b>	MIN.RATED REFERENCE CAPAC.	<b>30 / 20 Ah</b>	WEIGHT	<b>7,2 kg</b>

## SUPPLIED ACCESSORIES

123985	WORK CABLE 2,5 MMQ 1,5 M
123986	POSITIVE CABLE 2,5 MMQ 1,5 M
712623	COLORADO 40R POSITIVE CLAMP 40A
712624	COLORADO 40B WORK CLAMP 40A

## OPTIONAL ACCESSORIES

<b>BATTERY CHARGERS FUSES</b>	
802257	FUSES 20A 10 PCS

## DESCRIPTION

Battery charger with electronic control of the charging current, automatic interruption and restart (TRONIC), for charging lead-acid batteries with 12V/24V voltage.

Fit with switches to choose either anormal charge (MIN) or quick charge (BOOST) in the buffer mode (TRONIC) or drooping characteristic mode (CHARGE).

The buffer automatic charge is adequate for maintenance free sealed batteries (GEL/AGM/START-STOP), while the drooping characteristic charge is adequate for free-electrolyte batteries (WET).

Features:

- choice of output voltage, type of charge, charging mode
- display of charging current
- protection against overloads and polarity reversal.

## DOWNLOAD



CATALOG IMAGE



INSTRUCTION MANUAL



SPARE PARTS LIST