



- Battery charger and starter for 12/24V WET batteries and rapid cranking of all types of cars, vans, light goods vehicles, excavators, tractors and lorries.
- Fast (BOOST) charge and rapid cranking.
- Remote control. Timer to program timed BOOST charge and avoid overloading the battery.



- Display of charging and cranking current.
- Protection against overcharging and pole inversion.

TECHNICAL DATA

CODE	829009	CHARGE AND STARTING VOLTAGE	12 / 24 V	MIN.RATED REFERENCE CAPAC.	70 Ah
THREEPHASE MAINS VOLTAGE	230 / 400 V	EFFICIENT CHARGING CURRENT	150 / 250 A	MAX.RATED REFERENCE CAPAC.	2200 / 4000 Ah
MAINS FREQUENCY	50 / 60 Hz	RATED CHAR.CUR.EN60335-2-29	130 / 220 A	ADJUSTMENT POSITIONS	6
CHARGING ABSORBED POWER	7 kW	START CUR.1V/C EN60335-2-29	1000 / 1300 A	DIMENSIONS (LxWxH)	38 x 56 x 88,5 cm
STARTING ABSORBED POWER	44 kW	MAX STARTING CURRENT	1700 / 2000 A	WEIGHT	69 kg

SUPPLIED ACCESSORIES

123993	REMOTE CONTROL 6 M
713260	CABLE 50MMQ 3M-WORK CLAMP
713162	CABLE 50MMQ 3M-POSITIVE CLAMP-EYELET Ø10

OPTIONAL ACCESSORIES

BATTERY CHARGERS FUSES

802129	FUSES 300A 10 PCS
--------	-------------------

DESCRIPTION

Battery charger and starter for charging free electrolyte batteries (WET) with 12V/24V voltage and starting all kinds of cars, vans, light trucks, earth moving equipment, tractors and trucks.

Features:

- choice of normal charge, quick charge (BOOST), quick start
- timer for quick charge
- remote control
- display of charging and starting current
- protection against overloads and polarity reversal.

DOWNLOAD



CATALOG IMAGE



INSTRUCTION MANUAL



SPARE PARTS LIST