



Charger

6V

12V

24V

36V

48V



- Professional battery charger for WET/START-STOP 6/12/24/36/48V batteries. With ammeter and voltmeter.
- Allows simultaneous charging of multiple batteries connected in series.

TECHNICAL DATA

CODE	807063	CHARGING VOLTAGE	6/12/24/36/48 V	MAX.RATED REFERENCE CAPAC.	100/300/300/300/300Ah
SINGLEPHASE MAINS VOLTAGE	230 V	EFFICIENT CHARGING CURRENT	11/30/30/30/27 A	ADJUSTMENT POSITIONS	6
MAINS FREQUENCY	50 / 60 Hz	RATED CHAR.CUR.EN60335-2-29	7/20/20/20/18 A	DIMENSIONS (LxWxH)	28 x 35 x 32 cm
CHARGING ABSORBED POWER	1000 W	MIN.RATED REFERENCE CAPAC.	10 Ah	WEIGHT	12,7 kg

SUPPLIED ACCESSORIES

123569	CABLE 6 MMQ 2 M AND WORK CLAMP
123588	CABLE 6MMQ 2 M POSITIVE CLAMP

OPTIONAL ACCESSORIES

BATTERY CHARGERS FUSES	
802258	FUSES 30A 20 PCS

DESCRIPTION

Professional battery charger for charging all types of batteries (WET) with 6/12/24/36/48V voltage.
With protection against overloads and polarity reversal.
Allows simultaneous charging of several batteries in series.
Equipped with ammeter and voltmeter.

DOWNLOAD



CATALOG IMAGE



INSTRUCTION MANUAL



SPARE PARTS LIST



CERTIFICATE