

ALPINE 50 BOOST



12V

24V



- Battery charger for WET 12/24V batteries. With ammeter and normal or fast (BOOST) charge selector. 1000W.
- Protection against overcharging and pole inversion.

TECHNICAL DATA

CODE	807548	CHARGING VOLTAGE	12 / 24 V	MAX.RATED REFERENCE CAPAC.	500 Ah
SINGLEPHASE MAINS VOLTAGE	230 V	EFFECTIVE CHARGING CURRENT	45 A	ADJUSTMENT POSITIONS	4
MAINS FREQUENCY	50 / 60 Hz	RATED CHAR.CUR.EN60335-2-29	31 A	DIMENSIONS (LxWxH)	26,5 x 34,5 x 23 cm
CHARGING ABSORBED POWER	1000 W	MIN.RATED REFERENCE CAPAC.	20 Ah	WEIGHT	9,9 kg

SUPPLIED ACCESSORIES

123569	CABLE 6 MMQ 2 M AND WORK CLAMP
123581	CABLE 6MMQ 2 M POSITIVE CLAMP

OPTIONAL ACCESSORIES

BATTERY CHARGERS FUSES
802259 FUSES 50A 20 PCS

DESCRIPTION

Battery charger for charging free electrolyte batteries (WET) with 12V/24V voltage.
Protected against overloads and polarity reversal.
Equipped with selector for normal or quick (BOOST) charge. Equipped with ammeter.

DOWNLOAD



CATALOG IMAGE



INSTRUCTION MANUAL



SPARE PARTS LIST